

## Z-Wave Protocol Implementation Conformance Statement

### homee Z-Wave 700 Series Cube

#### General Information

<b>Product Identifier:</b>	HOMEE-005
<b>Brand Name:</b>	homee
<b>Product Version:</b>	HW: 3 FW: 7.15:07.15
<b>Z-Wave Certification #:</b>	ZC12-21090308

#### Product Features

<b>Gateway Has Preferred Partners</b>	No
<b>Firmware Updatable</b>	Not Updatable
<b>Communications Protocol</b>	Manufacturer Proprietary Protocol
<b>Communications Connections</b>	(No feature option values set for this feature)
<b>Supported Notification Types</b>	(No feature option values set for this feature)
<b>Sensors</b>	(No feature option values set for this feature)
<b>Supported Meter Type</b>	(No feature option values set for this feature)

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Access Control, S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## homee Z-Wave 700 Series Cube

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x3800
<b>Z-Wave Product Type:</b>	0x0013
<b>Z-Wave Hardware Platform:</b>	EFR32Z
<b>Z-Wave Development Kit Version:</b>	7.15.4
<b>Z-Wave Library Type:</b>	Bridge Controller
<b>Z-Wave Device Type / Role Type:</b>	Gateway / Central Static Controller

### Association Group Information

**Group # / Max**    **Description**

**Nodes**

1 / 1                    homee supports the association group 1 (Lifeline). A maximum number of 1 node can be added to this association group. The only event sent to this group is the device reset locally notification.

**Supported Command Classes (21):**

Application Status	Association Group Information V3
Association V3	CRC16 Encapsulation
Device Reset Locally	Firmware Update Meta-Data V5
Inclusion Controller	Indicator V3
Manufacturer Specific V2	Multi-Channel Association V4
Multi-Command	Network Management Basic V2
Node Provisioning	Powerlevel
Security S0	Security S2
Supervision	Time
Transport Service V2	Version V3
Z-Wave Plus Info V2	

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## homee Z-Wave 700 Series Cube

### Controlled Command Classes (33):

Anti-Theft Unlock	Association Group Information V3
Association V3	Basic V2
Battery	Central Scene V3
Configuration V4	CRC16 Encapsulation
Door Lock V4	Firmware Update Meta-Data V5
Indicator V3	Meter V5
Multi-Channel Association V4	Multi-Channel V4
Network Management Basic V2	Node Provisioning
Notification V8	Powerlevel
Security S0	Security S2
Sensor Alarm	Sensor Binary V2
Sensor Multilevel V11	Switch Binary V2
Switch Color V3	Switch Multilevel V4
Thermostat Mode V3	Thermostat Setback
Thermostat Setpoint	Thermostat Setpoint V3
Version V3	Wake Up V2
Z/IP V4	