

Z-Wave Protocol Implementation Conformance Statement

In Wall Roller shutter Controller

General Information

Product Identifier:	PAN34-JP
Brand Name:	Philio
Product Version:	HW: 1 FW: 1.01
Z-Wave Certification #:	ZC12-21080287

Product Features

Color	White
Firmware Updatable	Updatable by Consumer by RF
Window Covering Control Features	Automatic Calibration Position Aware Supports Open/Close Motion

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	Japan
Z-Wave Product ID:	0x0080
Z-Wave Product Type:	0x0001
Z-Wave Hardware Platform:	ZGM130
Z-Wave Development Kit Version:	7.15.1
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Window Covering DT / Always On Slave

Association Group Information

Group # / Max	Description
---------------	-------------

Z-Wave Protocol Implementation Conformance Statement

(Continued)

In Wall Roller shutter Controller

Supported Command Classes (20):

Association Group Information V3

Basic V2

Device Reset Locally

Indicator V3

Meter V3

Notification V8

Security S0

Supervision

Transport Service V2

Window Covering

Association V2

Configuration V4

Firmware Update Meta-Data V5

Manufacturer Specific V2

Multi-Channel Association V3

Powerlevel

Security S2

Switch Multilevel V4

Version V3

Z-Wave Plus Info V2