



Z-Wave Protocol Implementation Conformance Statement

In Wall Roller shutter Controller

General Information

Product Identifier:	PAN34-KR
Brand Name:	Philio
Product Version:	HW: 1 FW: 1.01
Z-Wave Certification #:	ZC12-21080288

Product Features

Color	White
Firmware Updatable	Updatable by Consumer by RF
Window Covering Control Features	Automatic Calibration Position Aware Supports Open/Close Motion

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	Taiwan, Singapore, South Korea, Thailand
Z-Wave Product ID:	0x0080
Z-Wave Product Type:	0x0001
Z-Wave Hardware Platform:	ZGM130
Z-Wave Development Kit Version:	7.15.1
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Window Covering DT / Always On Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

In Wall Roller shutter Controller

Association Group Information

Group # / Max **Description**

Nodes

1 / 5 There is only one group called Lifeline there is only 5 nodes for Group1 which support MULTILEVEL_SWITCH_REPORT METER_REPORT_COMMAND_V3 NOTIFICATION_REPORT and DEVICE_RESET_LOCALLY_NOTIFICATION.

Supported Command Classes (20):

- | | |
|----------------------------------|------------------------------|
| Association Group Information V3 | Association V2 |
| Basic V2 | Configuration V4 |
| Device Reset Locally | Firmware Update Meta-Data V5 |
| Indicator V3 | Manufacturer Specific V2 |
| Meter V3 | Multi-Channel Association V3 |
| Notification V8 | Powerlevel |
| Security S0 | Security S2 |
| Supervision | Switch Multilevel V4 |
| Transport Service V2 | Version V3 |
| Window Covering | Z-Wave Plus Info V2 |