

Z-Wave Protocol Implementation Conformance Statement

On/Off Plug

General Information

Product Identifier:	AN301-3
Brand Name:	Everspring
Product Version:	HW: 01 FW: 01.01:00.01
Z-Wave Certification #:	ZC13-21080001

Product Features

Firmware Updatable	Updatable by Consumer by RF
Switch Load Capacity Watts	Resistive load: Max 2990W
Electric Load Type	Fluorescent LED

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x0004
Z-Wave Product Type:	
Z-Wave Hardware Platform:	SD3502A-CNE3
Z-Wave Development Kit Version:	6.82.00
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max	Description
---------------	-------------

Z-Wave Protocol Implementation Conformance Statement

(Continued)

On/Off Plug

2 / 5

Supported Command Classes (16):

Association Group Information (AGI)	Association V2
Basic	Binary Switch
Configuration	Device Reset Locally
Firmware Update Meta Data V4	Manufacturer Specific V2
Multi Channel Association V3	Notification V8
Powerlevel	Security 2
Supervision	Transport Service V2
Version V3	Z-Wave Plus Info V2

Controlled Command Classes (1):

Basic