



## Z-Wave Protocol Implementation Conformance Statement

### 4 in 1 Multi-Sensor

#### General Information

Product Identifier:	PST10
Brand Name:	Philio
Product Version:	HW: 01 FW: 01.01:01.01
Z-Wave Certification #:	ZC14-21110020

#### Product Features

Battery Type	CR123A
Color	White
Firmware Updatable	Updatable by Consumer by RF

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

Z-Wave Frequency:	China
Z-Wave Product ID:	0x0085
Z-Wave Product Type:	0x0002
Z-Wave Hardware Platform:	ZGM130S037HGN2 / ZGM130S037HGN1
Z-Wave Development Kit Version:	7.15.1
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Notification Sensor DT / Reporting Sleeping Slave

#### Association Group Information

Group # / Max	Description
Nodes	

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## 4 in 1 Multi-Sensor

2 / 5

### Supported Command Classes (19):

Association Group Information (AGI) V3	Association V2
Battery	Configuration V4
Device Reset Locally	Firmware Update Meta Data V5
Indicator V3	Manufacturer Specific V2
Multi Channel Association V3	Multilevel Sensor V11
Notification V8	Powerlevel
Security 0	Security 2
Supervision	Transport Service V2
Version V3	Wake Up V2
Z-Wave Plus Info V2	