



Z-Wave Protocol Implementation Conformance Statement

Enbrighten Z-Wave Plus In-Wall Smart Dimmer, White and Light Almond

General Information

Product Identifier: 58438/ZWA3016
Brand Name: Enbrighten
Product Version: HW: 01 FW: 01.21
Z-Wave Certification #: ZC14-21110008

Product Features

Firmware Updatable Updatable by Consumer by RF
Z-Wave Scene Type Scene & Central Scene
Neutral Wire Required Yes

Z-Wave Product Information

Supports Z-Wave Beaming Technology? Yes
Supports Z-Wave Network Security? Yes
Supports Z-Wave AES-128 Security S0? No
Supports Security S2? Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible? Yes

Z-Wave Technical Information

Z-Wave Frequency: U.S. / Canada / Mexico
Z-Wave Product ID: 0x3430
Z-Wave Product Type: 0x4944
Z-Wave Hardware Platform: ZGM130S037HGN2 / ZGM130S037HGN1
Z-Wave Development Kit Version: 7.15.4
Z-Wave Library Type: Enhanced 232 Slave
Z-Wave Device Type / Role Type: Multilevel Switch DT / Always On Slave

Association Group Information

Group # / Max Nodes	Description
---------------------	-------------

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Enbrighten Z-Wave Plus In-Wall Smart Dimmer, White and Light Almond Paddles, 700S

2 / 5

3 / 5

Supported Command Classes (17):

Association Group Information (AGI) V3

Basic V2

Configuration V4

Firmware Update Meta Data V5

Manufacturer Specific V2

Multilevel Switch V4

Security 2

Transport Service V2

Z-Wave Plus Info V2

Association V2

Central Scene V3

Device Reset Locally

Indicator V3

Multi Channel Association V3

Powerlevel

Supervision

Version V3