

Z-Wave Protocol Implementation Conformance Statement

In Wall Micro Dimmer

General Information

Product Identifier:	PAD19-EU
Brand Name:	Philio
Product Version:	HW: 01 FW: 01.03:01.02
Z-Wave Certification #:	ZC14-22030072

Product Features

Color	White
Firmware Updatable	Updatable by Consumer by RF

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	South Africa, UAE, CEPT (Europe), Bahrain, Cyprus, Moldova, Egypt, French Guiana, Georgia, Iraq, Jordan, Kazakstan, Kuwait, Lebanon, Libya, Maldives, Mauritius, Nigeria, Oman, Philippines, Qatar, Saudi Arabia, Turkmenistan, Uzbekistan, Yemen, Algeria, Armenia
Z-Wave Product ID:	0x0005
Z-Wave Product Type:	
Z-Wave Hardware Platform:	ZGM130S037HGN2 / ZGM130S037HGN1
Z-Wave Development Kit Version:	7.16.3
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Multilevel Switch DT / Always On Slave

Association Group Information

Group # / Max Nodes	Description
---------------------	-------------

Z-Wave Protocol Implementation Conformance Statement

(Continued)

In Wall Micro Dimmer

2 / 5

Supported Command Classes (18):

Association Group Information (AGI) V3	Association V2
Basic V2	Configuration V4
Device Reset Locally	Firmware Update Meta Data V5
Indicator V3	Manufacturer Specific V2
Multi Channel Association V3	Multilevel Switch V4
Notification V8	Powerlevel
Security 0	Security 2
Supervision	Transport Service V2
Version V3	Z-Wave Plus Info V2