



## Z-Wave Protocol Implementation Conformance Statement

# JascoPro Series Z-Wave Plus™ In-Wall Smart Switch, White Toggle,

### General Information

<b>Product Identifier:</b>	60517/ZWA4012DV
<b>Brand Name:</b>	JascoPro Series
<b>Product Version:</b>	HW: 01 FW: 01.21
<b>Z-Wave Certification #:</b>	ZC14-22020063

### Product Features

<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Neutral Wire Required</b>	Yes
<b>Switch Load Capacity Watts</b>	960W incandescent
<b>Switch Type</b>	Toggle
<b>Z-Wave Scene Type</b>	Scene & Central Scene

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico, U.S. / Canada / Mexico, U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x3338
<b>Z-Wave Product Type:</b>	0x4952
<b>Z-Wave Hardware Platform:</b>	ZGM130S037HGN2 / ZGM130S037HGN1
<b>Z-Wave Development Kit Version:</b>	7.15.4
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Binary Switch DT / Always On Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

JascoPro Series Z-Wave Plus™ In-Wall Smart Switch, White Toggle, 120/277, 700S

## Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 5

2 / 5

3 / 5

**Supported Command Classes (19):**

- |  |                              |
|--|------------------------------|
| Association Group Information (AGI) V3 | Association V2               |
| Basic V2                               | Binary Switch V2             |
| Central Scene V3                       | Configuration V4             |
| Device Reset Locally                   | Firmware Update Meta Data V5 |
| Indicator V3                           | Manufacturer Specific V2     |
| Multi Channel Association V3           | Powerlevel                   |
| Scene Activation                       | Scene Actuator Configuration |
| Security 2                             | Supervision                  |
| Transport Service V2                   | Version V3                   |
| Z-Wave Plus Info V2                    |                              |