

## Z-Wave Protocol Implementation Conformance Statement

### Dry Contact Relay

#### General Information

<b>Product Identifier:</b>	ZEN51
<b>Brand Name:</b>	Zooz
<b>Product Version:</b>	HW: 01 FW: 01.21
<b>Z-Wave Certification #:</b>	ZC14-22040094

#### Product Features

<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Neutral Wire Required</b>	Yes
<b>Switch Load Capacity Current</b>	10
<b>Switch Type</b>	Dry Contact
<b>Z-Wave Scene Type</b>	Central Scene

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico, U.S. / Canada / Mexico, U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0104
<b>Z-Wave Product Type:</b>	
<b>Z-Wave Hardware Platform:</b>	ZGM130S037HGN2 / ZGM130S037HGN1
<b>Z-Wave Development Kit Version:</b>	7.15.4
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Binary Switch DT / Always On Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Dry Contact Relay

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 5

2 / 5

**Supported Command Classes (18):**

Application Status	Association Group Information (AGI) V3
Association V2	Basic V2
Binary Switch V2	Central Scene V3
Configuration V4	Device Reset Locally
Firmware Update Meta Data V5	Indicator V3
Manufacturer Specific V2	Multi Channel Association V3
Powerlevel	Security 2
Supervision	Transport Service V2
Version V3	Z-Wave Plus Info V2