

Z-Wave Protocol Implementation Conformance Statement

Zooz 4-in-1 Sensor 700 Series

General Information

Product Identifier:	ZSE40AU-700
Brand Name:	Zooz
Product Version:	HW: 3 FW: 32.32
Z-Wave Certification #:	ZC12-22040335

Product Features

Firmware Updatable	Updatable by Consumer by RF
Battery Quantity	1
Battery Type	CR123A
Color	White

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	Australia / New Zealand, Malaysia, Brazil, Australia / New Zealand
Z-Wave Product ID:	0x2101
Z-Wave Product Type:	0x2021
Z-Wave Hardware Platform:	ZGM130
Z-Wave Development Kit Version:	7.13.6
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Notification Sensor / Reporting Sleeping Slave

Association Group Information

Group # / Max	Description
---------------	-------------

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Zooz 4-in-1 Sensor 700 Series

2 / 5 The 4-in-1 sensor supports Group 2 with up to five devices for basic set reports.

Supported Command Classes (20):

Application Status	Association Group Information (AGI) V3
Association V2	Battery
Configuration V4	Device Reset Locally
Firmware Update Meta Data V5	Indicator V3
Manufacturer Specific V2	Multi Channel Association V3
Multilevel Sensor V11	Notification V8
Powerlevel	Security 0
Security 2	Supervision
Transport Service V2	Version V3
Wake Up V2	Z-Wave Plus Info V2