

Z-Wave Protocol Implementation Conformance Statement

TILT | SHOCK XS SENSOR

General Information

Product Identifier:	ZSE43
Brand Name:	Zooz
Product Version:	HW: 01 FW: 01.00
Z-Wave Certification #:	ZC14-22040100

Product Features

Battery Quantity	1
Battery Type	CR2032
Firmware Updatable	Updatable by Consumer by RF

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico, U.S. / Canada / Mexico, U.S. / Canada / Mexico
Z-Wave Product ID:	0x7000
Z-Wave Product Type:	
Z-Wave Hardware Platform:	ZGM130S037HGN2 / ZGM130S037HGN1
Z-Wave Development Kit Version:	7.16.3
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Notification Sensor DT / Reporting Sleeping Slave

Association Group Information

Group # / Max	Description
Nodes	

Z-Wave Protocol Implementation Conformance Statement

(Continued)

TILT | SHOCK XS SENSOR

2 / 5

3 / 5

Supported Command Classes (18):

Association Group Information (AGI) V3

Battery

Configuration V4

Firmware Update Meta Data V5

Manufacturer Specific V2

Notification V8

Security 2

Transport Service V2

Wake Up V2

Association V2

Binary Sensor V2

Device Reset Locally

Indicator V3

Multi Channel Association V3

Powerlevel

Supervision

Version V3

Z-Wave Plus Info V2