

## Z-Wave Protocol Implementation Conformance Statement

### T6 Pro Z-Wave with SmartStart

#### General Information

<b>Product Identifier:</b>	TH6320ZW2007
<b>Brand Name:</b>	Honeywell Home (Resideo)
<b>Product Version:</b>	HW: 01 FW: 03.00:03.01
<b>Z-Wave Certification #:</b>	ZC14-22040099

#### Product Features

<b>Battery Quantity</b>	3
<b>Battery Type</b>	AA
<b>Thermostat HVAC Systems Supported</b>	Cool Only Dual Fuel Heat Only Heat Pump Multi Stage Single Stage Universal
<b>Thermostat Modes</b>	Auto Auto Changeover Auxiliary/Emergency Heat Away Cool Energy Save Cool Energy Save Heat Fan Only
<b>Thermostat Power Source</b>	Battery Power Stealing (hard-wired 24V)

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## T6 Pro Z-Wave with SmartStart

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico, U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0011
<b>Z-Wave Product Type:</b>	
<b>Z-Wave Hardware Platform:</b>	ZGM130S037HGN2 / ZGM130S037HGN1
<b>Z-Wave Development Kit Version:</b>	7.16.3
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Thermostat DT / Listening Sleeping Slave

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 1

**Supported Command Classes (24):**

Association Group Information (AGI) V3	Association V2
Basic V2	Battery
Clock	Configuration V4
Device Reset Locally	Firmware Update Meta Data V5
Indicator V3	Manufacturer Specific V2
Multi Channel Association V3	Multilevel Sensor V5
Notification V3	Powerlevel
Security 2	Supervision
Thermostat Fan Mode V3	Thermostat Fan State
Thermostat Mode V3	Thermostat Operating State
Thermostat Setpoint V2	Transport Service V2
Version V3	Z-Wave Plus Info V2