

## Z-Wave Protocol Implementation Conformance Statement

# Yale NexTouch Keypad Exit Rim Trim

### General Information

<b>Product Identifier:</b>	NTT612-ZW2
<b>Brand Name:</b>	Yale Locks & Hardware
<b>Product Version:</b>	HW: 255 FW: 1.78:32.33
<b>Z-Wave Certification #:</b>	ZC10-22067113

### Product Features

#### Battery Type

#### Battery Quantity

#### Door Lock Type

Deadbolt

#### Firmware Updatable

Not Updatable

#### IP (Ingress Protection) Rated

No

#### Outdoor Use

No

#### Sensors

(No feature option values set for this feature)

#### Supported Notification Types

(No feature option values set for this feature)

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Yale NexTouch Keypad Exit Rim Trim

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0C0C
<b>Z-Wave Product Type:</b>	0x8102
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.51.07
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Door Lock - Keypad / Listening Sleeping Slave

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 1                Z-Wave Plus Lifeline

**Supported Command Classes (18):**

Association Group Info	Association V2
Battery	Configuration
Device Reset Locally	Door Lock Logging
Door Lock V2	Firmware Update Meta-Data V3
Manufacturer Specific V2	Notification V4
Powerlevel	Schedule Entry Lock V3
Security 0	Time Parameters
Time V2	User Code
Version V2	Z-Wave Plus Info V2