

Z-Wave Protocol Implementation Conformance Statement

Z-Wave Mini Plug

General Information

Product Identifier:	MP31Z
Brand Name:	Minoston
Product Version:	HW: 01 FW: 01.00
Z-Wave Certification #:	ZC14-22070113

Product Features

Electric Load Type	Dimmable LED ELV (Electronic) Incandescent Inductive (e.g. Motor) LED MLV (Magnetic)
Firmware Updatable	Updatable by Consumer by RF
Switch Type	Toggle

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico, U.S. / Canada / Mexico, U.S. / Canada / Mexico
Z-Wave Product ID:	0xFF0C
Z-Wave Product Type:	0xFF00
Z-Wave Hardware Platform:	ZGM130S037HGN2 / ZGM130S037HGN1
Z-Wave Development Kit Version:	7.16.3
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Binary Switch DT / Always On Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Z-Wave Mini Plug

Association Group Information

Group # / Max Description

Nodes

1 / 5

Supported Command Classes (23):

- | | |
|--|------------------------------|
| Association Group Information (AGI) V3 | Association V2 |
| Basic V2 | Binary Switch V2 |
| Clock | Color Switch V3 |
| Configuration V4 | Device Reset Locally |
| Firmware Update Meta Data V5 | Indicator V3 |
| Manufacturer Specific V2 | Multi Channel Association V3 |
| Multi Channel V4 | Multilevel Switch V4 |
| Notification V8 | Powerlevel |
| Scene Activation | Scene Actuator Configuration |
| Security 2 | Supervision |
| Transport Service V2 | Version V3 |
| Z-Wave Plus Info V2 | |