

Z-Wave Protocol Implementation Conformance Statement

700 Series Outdoor Double Plug

General Information

Product Identifier:	ZEN14
Brand Name:	Zooz
Product Version:	HW: 255 FW: 1.01
Z-Wave Certification #:	ZC10-22087116

Product Features

Color	Black
Electric Load Type	Incandescent Inductive (e.g. Motor) LED
Firmware Updatable	Updatable by Consumer by RF
Switch Load Capacity Current	15
Switch Load Capacity Watts	960

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0xB003
Z-Wave Product Type:	0x7000
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.71.01
Z-Wave Library Type:	Enhanced 232 Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

700 Series Outdoor Double Plug

Association Group Information

Group # / Max **Description**

Nodes

- 1 / 1 Lifeline communication to the controller (Lifeline).
- 2 / 2 Basic set control of associated devices.
- 3 / 2 Basic set control of associated devices.

Supported Command Classes (17):

- | | |
|--------------------------|------------------------------|
| Association Group Info | Association V2 |
| Basic V2 | Binary Switch |
| Configuration | Firmware Update Meta Data V4 |
| Manufacturer Specific V2 | Multi Channel Association V3 |
| Multi Channel V4 | Notification V8 |
| Powerlevel | Security 0 |
| Security 2 | Supervision |
| Transport Service V2 | Version V2 |
| Z-Wave Plus Info V2 | |

Controlled Command Classes (1):

- Basic V2