

Z-Wave Protocol Implementation Conformance Statement

Ness Z-Wave Single Button

General Information

Product Identifier:	ZA-116011
Brand Name:	Ness
Product Version:	HW: 01 FW: 01.01
Z-Wave Certification #:	ZC14-22090132

Product Features

Battery Type	CR2450
Color	White
Switch Type	Push Button

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	Australia / New Zealand, Australia / New Zealand
Z-Wave Product ID:	0x0601
Z-Wave Product Type:	0x0204
Z-Wave Hardware Platform:	ZGM130S037HGN2 / ZGM130S037HGN1
Z-Wave Development Kit Version:	7.16.3
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Central Scene DT / Reporting Sleeping Slave

Association Group Information

Group # / Max	Description
Nodes	

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Ness Z-Wave Single Button

2 / 5

3 / 5

Supported Command Classes (19):

Application Status	Association Group Information (AGI) V3
Association V2	Battery
Central Scene V3	Configuration V4
Device Reset Locally	Firmware Update Meta Data V5
Indicator V3	Manufacturer Specific V2
Multi Channel Association V3	Powerlevel
Security 0	Security 2
Supervision	Transport Service V2
Version V3	Wake Up V2
Z-Wave Plus Info V2	