

Z-Wave Protocol Implementation Conformance Statement

Water Dragon

General Information

| | |
|--------------------------------|------------------------|
| Product Identifier: | ADC-SHM-100-A |
| Brand Name: | Alarm.com |
| Product Version: | HW: 01 FW: 00.25:00.20 |
| Z-Wave Certification #: | ZC14-22100149 |

Z-Wave Product Information

| | |
|--------------------------------------|---|
| Supports Z-Wave Beaming Technology? | Yes |
| Supports Z-Wave Network Security? | Yes |
| Supports Z-Wave AES-128 Security S0? | No |
| Supports Security S2? | Yes: S2 Authenticated, S2 Unauthenticated |
| SmartStart Compatible? | Yes |

Z-Wave Technical Information

| | |
|--|---|
| Z-Wave Frequency: | U.S. / Canada / Mexico, US_LR, U.S. / Canada / Mexico |
| Z-Wave Product ID: | 0x0007 |
| Z-Wave Product Type: | |
| Z-Wave Hardware Platform: | ZGM130S037HGN2 / ZGM130S037HGN1 |
| Z-Wave Development Kit Version: | 7.16.3 |
| Z-Wave Library Type: | Enhanced 232 Slave |
| Z-Wave Device Type / Role Type: | Notification Sensor DT / Always On Slave |

Association Group Information

Group # / Max Description

Nodes

1 / 4

Supported Command Classes (17):

| | |
|--|-----------------------|
| Association Group Information (AGI) V3 | Association V2 |
| Configuration V4 | Device Reset Locally |
| Firmware Update Meta Data V5 | Indicator V3 |
| Manufacturer Specific V2 | Meter V2 |
| Multi Channel Association V3 | Multilevel Sensor V11 |
| Notification V8 | Powerlevel |
| Security 2 | Supervision |
| Transport Service V2 | Version V3 |