

Z-Wave Protocol Implementation Conformance Statement

Venture WISE Window Sensor

General Information

Product Identifier:	FGDW-002
Brand Name:	Venture WISE
Product Version:	HW: 2 FW: 3.02
Z-Wave Certification #:	ZC10-22127118

Product Features

Battery Quantity	1
Battery Type	ER14250 or CR2
Firmware Updatable	Updatable by Consumer by RF
Sensors	Air Temperature
Supported Notification Types	Access Control Heat Alarm Home Security Power Management

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x1000
Z-Wave Product Type:	0x0702
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.51.09

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Venture WISE Window Sensor

Association Group Information

Group # / Max Description

Nodes

- 1 / 1 "Lifeline" reports the device status and allows for assigning single device only (main controller by default).
- 2 / 5 "On/Off" is assigned to the device status - contact sensor (sends Basic Set command frames).
- 3 / 5 "Tamper" is assigned to the TMP switch (sends alarm command frames).

Supported Command Classes (18):

Application Status	Association Group Info
Association V2	Basic
Battery	Configuration
CRC-16 Encapsulation	Device Reset Locally
Firmware Update Meta Data V4	Manufacturer Specific V2
Multi Channel Association V3	Multilevel Sensor V5
Notification V5	Powerlevel
Security 0	Version V2
Wake Up V2	Z-Wave Plus Info V2

Controlled Command Classes (2):

Basic	Notification V5
-------	-----------------