

Z-Wave Protocol Implementation Conformance Statement

Thermostatic Radiator Valve

General Information

Product Identifier: Z-TRV-V01
Brand Name: ZVIDAR
Product Version: HW: 01 FW: 01.08
Z-Wave Certification #: ZC14-23050241

Product Features

Firmware Updatable Updatable by Professional/Technician
Thermostat Modes (No feature option values set for this feature)

Z-Wave Product Information

Supports Z-Wave Beaming Technology? Yes
 Supports Z-Wave Network Security? Yes
 Supports Z-Wave AES-128 Security S0? Yes
 Supports Security S2? Yes: S2 Authenticated, S2 Unauthenticated
 SmartStart Compatible? Yes

Z-Wave Technical Information

Z-Wave Frequency: Taiwan, Chile, Australia / New Zealand, Brazil, China, Columbia, Hong Kong, India, Israel, Japan, Malaysia, Russia, Singapore, South Africa, South Korea, UAE, U.S. / Canada / Mexico, CEPT (Europe), El Salvador, Indonesia, Australia / New Zealand, Paraguay, Peru, Uruguay, Venezuela, Vietnam, Morocco, Thailand, Bahrain, Cyprus, Moldova, Egypt, French Guiana, Georgia, Iraq, Jordan, Kazakstan, Kuwait, Lebanon, Libya, Maldives, Mauritius, Nigeria, Oman, Philippines, Qatar, Saudi Arabia, Turkmenistan, Uzbekistan, Yemen, Algeria, Armenia, Costa Rica, Macau, Argentina, Bahamas, Barbados, Bermuda, Bolivia, British Virgin Islands, U.S. / Canada / Mexico, U.S. / Canada / Mexico, Cayman Islands, Ecuador, Guatemala, Haiti, Honduras, Jamaica, Panama, St Kitts and Nevis, Suriname, Trinidad and Tabago, Turks and Caicos Islands

Z-Wave Product ID: 0x0501
Z-Wave Product Type: 0x0400
Z-Wave Hardware Platform: ZCM120S027LHCN3 / ZCM120S027LHCN4
Group # / Max Description
Nodes
Z-Wave Library Type: LIMITED END NODE Z32

Association Group Information

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Thermostatic Radiator Valve

Supported Command Classes (21):

Application Status	Association Group Information (AGI) V3
Association V2	Basic V2
Battery	Configuration V4
Device Reset Locally	Firmware Update Meta Data V5
Indicator V3	Manufacturer Specific V2
Multi Channel Association V3	Multilevel Sensor V11
Powerlevel	Security 0
Security 2	Supervision
Thermostat Mode V3	Thermostat Setpoint V3
Transport Service V2	Version V3
Z-Wave Plus Info V2	