

Z-Wave Protocol Implementation Conformance Statement

Decora Smart Z-Wave™ 800 Series Switch

General Information

Product Identifier:	ZW15S
Brand Name:	Leviton
Product Version:	HW: 01 FW: 01.00:02.01
Z-Wave Certification #:	ZC14-23070303

Product Features

Electric Load Type	ELV (Electronic) Fluorescent Incandescent Inductive (e.g. Motor) LED MLV (Magnetic)
Firmware Updatable	Updatable by Consumer by RF
Neutral Wire Required	Yes
Switch Load Capacity Watts	1500W Incandescent / Halogen
Switch Type	Decorator Paddle Push with Indicator
Z-Wave Scene Type	Scene
Switch Load Capacity Current	15A General Use, 5A LED/CFL/Electronic Ballast, 15A Magnetic Ballast

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Decora Smart Z-Wave™ 800 Series Switch

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico, U.S. / Canada / Mexico, U.S. / Canada / Mexico
Z-Wave Product ID:	0x0042
Z-Wave Product Type:	
Z-Wave Hardware Platform:	ZGM230SA
Z-Wave Development Kit Version:	7.18.3
Z-Wave Library Type:	Enhanced End Node 232
Z-Wave Device Type / Role Type:	Binary Switch DT / Always On End Node

Association Group Information

Group # / Max Description

Nodes

1 / 5

2 / 5

3 / 5

Supported Command Classes (18):

Association Group Information (AGI) V3	Association V2
Basic V2	Binary Switch V2
Configuration V4	Device Reset Locally
Firmware Update Meta Data V5	Indicator V3
Manufacturer Specific V2	Multi Channel Association V3
Powerlevel	Scene Activation
Scene Actuator Configuration	Security 2
Supervision	Transport Service V2
Version V3	Z-Wave Plus Info V2