



## Z-Wave Protocol Implementation Conformance Statement

# Z-Wave Plus In-Wall Smart Switch, White and Light Almond Paddles

## General Information

<b>Product Identifier:</b>	76596/ZWN4015
<b>Brand Name:</b>	Jasco Pro Series
<b>Product Version:</b>	HW: 01 FW: 00.03
<b>Z-Wave Certification #:</b>	ZC14-23080313

## Product Features

<b>Color</b>	White
<b>Electric Load Type</b>	Incandescent Inductive (e.g. Motor) LED
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Switch Load Capacity Current</b>	15A

## Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

## Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico, US_LR, U.S. / Canada / Mexico, U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x4952
<b>Z-Wave Product Type:</b>	
<b>Z-Wave Hardware Platform:</b>	EFR32ZG23A
<b>Z-Wave Development Kit Version:</b>	7.19.3
<b>Z-Wave Library Type:</b>	Enhanced End Node 232

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Z-Wave Plus In-Wall Smart Switch, White and Light Almond Paddles, 800S

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 5

2 / 5

3 / 5

**Supported Command Classes (17):**

Association Group Information (AGI) V3

Basic V2

Central Scene V3

Device Reset Locally

Indicator V3

Multi Channel Association V3

Security 2

Transport Service V2

Z-Wave Plus Info V2

Association V2

Binary Switch V2

Configuration V4

Firmware Update Meta Data V5

Manufacturer Specific V2

Powerlevel

Supervision

Version V3