



Z-Wave Protocol Implementation Conformance Statement

Z-Wave Plus In-Wall Smart Switch, White and Light Almond Paddles

General Information

Product Identifier:	76601/ZWN4015
Brand Name:	UltraPro
Product Version:	HW: 01 FW: 00.03
Z-Wave Certification #:	ZC14-23080318

Product Features

Color	White
Electric Load Type	Incandescent Inductive (e.g. Motor) LED
Firmware Updatable	Updatable by Consumer by RF
Switch Load Capacity Current	15A

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico, US_LR, U.S. / Canada / Mexico, U.S. / Canada / Mexico
Z-Wave Product ID:	0x4952
Z-Wave Product Type:	
Z-Wave Hardware Platform:	EFR32ZG23A
Z-Wave Development Kit Version:	7.19.3
Z-Wave Library Type:	Enhanced End Node 232

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Z-Wave Plus In-Wall Smart Switch, White and Light Almond Paddles, 800S

Association Group Information

Group # / Max Description

Nodes

1 / 5

2 / 5

3 / 5

Supported Command Classes (17):

- | | |
|--|------------------------------|
| Association Group Information (AGI) V3 | Association V2 |
| Basic V2 | Binary Switch V2 |
| Central Scene V3 | Configuration V4 |
| Device Reset Locally | Firmware Update Meta Data V5 |
| Indicator V3 | Manufacturer Specific V2 |
| Multi Channel Association V3 | Powerlevel |
| Security 2 | Supervision |
| Transport Service V2 | Version V3 |
| Z-Wave Plus Info V2 | |