

Z-Wave Protocol Implementation Conformance Statement

SMART PLUG

General Information

Product Identifier:	ZEN04 800LR
Brand Name:	Zooz
Product Version:	HW: 02 FW: 08.00
Z-Wave Certification #:	ZC14-23080322

Product Features

Color	White
Firmware Updatable	Updatable by Consumer by RF
Electric Load Type	Incandescent LED
Switch Load Capacity Current	15

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico, US_LR, U.S. / Canada / Mexico, U.S. / Canada / Mexico
Z-Wave Product ID:	0x7000
Z-Wave Product Type:	
Z-Wave Hardware Platform:	EFR32ZG23A
Z-Wave Development Kit Version:	7.19.2
Z-Wave Library Type:	Enhanced End Node 232
Z-Wave Device Type / Role Type:	Binary Switch DT / Always On End Node

Z-Wave Protocol Implementation Conformance Statement

(Continued)

SMART PLUG

Association Group Information

Group # / Max Description

Nodes

1 / 5

2 / 5

Supported Command Classes (18):

- | | |
|--|----------------------|
| Association Group Information (AGI) V3 | Association V2 |
| Basic V2 | Binary Switch V2 |
| Configuration V4 | Device Reset Locally |
| Firmware Update Meta Data V5 | Indicator V3 |
| Manufacturer Specific V2 | Meter V5 |
| Multi Channel Association V3 | Notification V8 |
| Powerlevel | Security 2 |
| Supervision | Transport Service V2 |
| Version V3 | Z-Wave Plus Info V2 |