



Z-Wave Protocol Implementation Conformance Statement

DC Signal Sensor

General Information

Product Identifier:	ZEN55 LR
Brand Name:	Zooz
Product Version:	HW: 01 FW: 01.11
Z-Wave Certification #:	ZC14-23090328

Product Features

Firmware Updatable	Updatable by Consumer by RF
Neutral Wire Required	Yes

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	US_LR, Columbia, U.S. / Canada / Mexico, Argentina, Bahamas, Barbados, Bermuda, Bolivia, British Virgin Islands, U.S. / Canada / Mexico, U.S. / Canada / Mexico, Cayman Islands, Ecuador, Guatemala, Haiti, Honduras, Jamaica, Panama, St Kitts and Nevis, Suriname, Trinidad and Tabago, Turks and Caicos Islands
Z-Wave Product ID:	0x0004
Z-Wave Product Type:	
Z-Wave Hardware Platform:	EFR32ZG23A
Z-Wave Development Kit Version:	7.18.3
Z-Wave Library Type:	Enhanced End Node 232
Z-Wave Device Type / Role Type:	Notification Sensor DT / Always On Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

DC Signal Sensor

Association Group Information

Group # / Max Description

Nodes

1 / 5

2 / 5

3 / 5

4 / 5

Supported Command Classes (19):

Application Status	Association Group Information (AGI) V3
Association V2	Basic V2
Binary Switch V2	Configuration V4
Device Reset Locally	Firmware Update Meta Data V5
Indicator V3	Manufacturer Specific V2
Multi Channel Association V3	Multi Channel V4
Notification V8	Powerlevel
Security 2	Supervision
Transport Service V2	Version V3
Z-Wave Plus Info V2	