

## Z-Wave Protocol Implementation Conformance Statement

### Security Camera

#### General Information

<b>Product Identifier:</b>	ACBUSREE
<b>Brand Name:</b>	Avigilon
<b>Product Version:</b>	HW: 01 FW: 07.18:07.18
<b>Z-Wave Certification #:</b>	ZC14-23100346

#### Product Features

<b>Color</b>	Light Gray
<b>Communications Connections</b>	Ethernet (Wired)
<b>Communications Protocol</b>	Z-Wave Z/IP
<b>Firmware Updatable</b>	Updatable by Professional/Technician
<b>IP (Ingress Protection) Rated</b>	Yes
<b>Outdoor Use</b>	Yes
<b>Z-Wave Scene Type</b>	Central Scene

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Access Control, S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Security Camera

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x0004
<b>Z-Wave Product Type:</b>	0x0001
<b>Z-Wave Hardware Platform:</b>	ZGM230SA
<b>Z-Wave Development Kit Version:</b>	7.18.1
<b>Z-Wave Library Type:</b>	Bridge Controller
<b>Z-Wave Device Type / Role Type:</b>	Gateway DT / Central Static Controller

### Association Group Information

**Group # / Max    Description**

#### Nodes

1 / 1

#### Supported Command Classes (24):

Application Status	Association Group Information (AGI) V3
Association V2	CRC-16 Encapsulation
Device Reset Locally	Firmware Update Meta Data V8
Inclusion Controller	Indicator V3
Manufacturer Specific V2	Multi Channel Association V3
Multi Command	Network Management Basic Node V2
Network Management Inclusion V4	Network Management Installation and Maintenance V4
Network Management Proxy V4	Node Provisioning
Powerlevel	Security 0
Security 2	Supervision V2
Time	Transport Service V2
Version V3	Z-Wave Plus Info V2

#### Controlled Command Classes (29):

Application Status	Association Group Information (AGI) V3
Association V2	Basic V2
Battery V3	Central Scene V3
CRC-16 Encapsulation	Device Reset Locally
Entry Control	Firmware Update Meta Data V8
Indicator V3	Manufacturer Specific V2
Meter V5	Multi Channel Association V3
Multi Channel V4	Multi Command
Multilevel Sensor V11	No Operation
Notification V8	Powerlevel
Security 0	Security 2
Supervision V2	Time
Transport Service V2	Version V3
Wake Up V3	Z/IP Naming and Location
Z-Wave Plus Info V2	