



Z-Wave Protocol Implementation Conformance Statement

Power Switch

General Information

Product Identifier: ZEN15 800LR
Brand Name: Zooz
Product Version: HW: 20 FW: 02.00
Z-Wave Certification #: ZC14-24010387

Product Features

Color White

Electric Load Type ELV (Electronic)
Incandescent
LED

Firmware Updatable Updatable by Consumer by RF

Switch Load Capacity Current 15

Z-Wave Product Information

Supports Z-Wave Beaming Technology? Yes
Supports Z-Wave Network Security? Yes
Supports Z-Wave AES-128 Security S0? Yes
Supports Security S2? Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible? Yes

Z-Wave Technical Information

Z-Wave Frequency: U.S. / Canada / Mexico, Columbia, US_LR, Argentina, Bahamas, Barbados, Bermuda, Bolivia, British Virgin Islands, U.S. / Canada / Mexico, U.S. / Canada / Mexico, Cayman Islands, Guatemala, Haiti, Honduras, Jamaica, Panama, St Kitts and Nevis, Suriname, Trinidad and Tabago, Turks and Caicos Islands

Z-Wave Product ID: 0x000D
Z-Wave Product Type: 0x0101

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Power Switch

Association Group Information

Group # / Max Description

Nodes

1 / 5

Supported Command Classes (21):

Application Status	Association Group Information (AGI) V3
Association V2	Basic V2
Binary Switch V2	Configuration V4
Device Reset Locally	Firmware Update Meta Data V5
Indicator V3	Manufacturer Specific V2
Meter V3	Multi Channel Association V3
Powerlevel	Scene Activation
Scene Actuator Configuration	Security 0
Security 2	Supervision
Transport Service V2	Version V3
Z-Wave Plus Info V2	