

## Z-Wave Protocol Implementation Conformance Statement

# 10 Button Z-Wave Plus v2 Deadbolt

### General Information

<b>Product Identifier:</b>	GED1800
<b>Brand Name:</b>	Weiser
<b>Product Version:</b>	HW: 1 FW: 10.20:69.35
<b>Z-Wave Certification #:</b>	ZC12-24050355

### Product Features

<b>Door Lock Type</b>	Deadbolt
<b>Firmware Updatable</b>	Not Updatable
<b>Battery Quantity</b>	4
<b>Battery Type</b>	AA

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Don't know
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Access Control
SmartStart Compatible?	Yes

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico, U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x06A8
<b>Z-Wave Product Type:</b>	0x0811
<b>Z-Wave Hardware Platform:</b>	ZGM130
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Lock / Listening Sleeping Slave

### Association Group Information

Group # / Max	Description
---------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## 10 Button Z-Wave Plus v2 Deadbolt

### Supported Command Classes (24):

Anti-theft V2	Association Group Information (AGI) V3
Association V2	Basic V2
Battery	Configuration V4
Device Reset Locally	Door Lock Logging
Door Lock V4	Firmware Update Meta Data V5
Indicator V3	Manufacturer Specific V2
Multi Channel Association V3	Notification V8
Powerlevel	Schedule Entry Lock V3
Security 0	Security 2
Supervision	Time Parameters
Transport Service V2	User Code V2
Version V3	Z-Wave Plus Info V2