

Z-Wave Protocol Implementation Conformance Statement

Wave PM Mini

General Information

Product Identifier:	QMEM-0A1PC16EU
Brand Name:	Shelly Qubino
Product Version:	HW: 01 FW: 10.07:02.02
Z-Wave Certification #:	ZC14-24070437

Product Features

Color	Light Gray
Firmware Updatable	Updatable by Consumer by RF
Neutral Wire Required	Yes
Switch Load Capacity Current	16 A
Switch Type	Toggle

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	South Africa, UAE, CEPT (Europe), Bahrain, Cyprus, Moldova, Egypt, French Guiana, Georgia, Iraq, Jordan, Kazakstan, Kuwait, Lebanon, Libya, Maldives, Mauritius, Nigeria, Oman, Philippines, Qatar, Saudi Arabia, Turkmenistan, Uzbekistan, Yemen, Armenia
Z-Wave Product ID:	0x0081
Z-Wave Product Type:	0x0007
Z-Wave Hardware Platform:	EFR32ZG23A
Z-Wave Development Kit Version:	7.19.1
Z-Wave Library Type:	Enhanced End Node 232

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Wave PM Mini

Association Group Information

Group # / Max Description

Nodes

1 / 9

Supported Command Classes (17):

Association Group Information (AGI) V3	Association V2
Configuration V4	Device Reset Locally
Firmware Update Meta Data V5	Indicator V3
Manufacturer Specific V2	Meter V6
Multi Channel Association V3	Notification V8
Powerlevel	Security 0
Security 2	Supervision
Transport Service V2	Version V3
Z-Wave Plus Info V2	