



Z-Wave Protocol Implementation Conformance Statement

Q Sensor

General Information

Product Identifier:	ZSE11 800LR
Brand Name:	Zooz
Product Version:	HW: 02 FW: 02.00
Z-Wave Certification #:	ZC14-24070454

Product Features

Battery Quantity	2
Battery Type	CR 123A
Color	White
Firmware Updatable	Updatable by Consumer by RF

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico, US_LR, U.S. / Canada / Mexico, U.S. / Canada / Mexico
Z-Wave Product ID:	0x0006
Z-Wave Product Type:	0x0201
Z-Wave Hardware Platform:	EFR32ZG23A
Z-Wave Development Kit Version:	7.18.8
Z-Wave Library Type:	Enhanced End Node 232
Z-Wave Device Type / Role Type:	Notification Sensor DT / Reporting Sleeping End Node

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Q Sensor

Association Group Information

Group # / Max Description

Nodes

1 / 5

2 / 5

Supported Command Classes (20):

Application Status	Association Group Information (AGI) V3
Association V2	Battery
Configuration V4	Device Reset Locally
Firmware Update Meta Data V5	Indicator V3
Manufacturer Specific V2	Multi Channel Association V3
Multilevel Sensor V11	Notification V8
Powerlevel	Security 0
Security 2	Supervision
Transport Service V2	Version V3
Wake Up V2	Z-Wave Plus Info V2